



Confidea T-CI

Confidea Tabletop Chairman Interpretation Unit



Description

The Confidea T-CI is Televic's tabletop chairman unit for discussion systems combined with simultaneous interpretation. It combines a slim, contemporary design and excellent intelligibility with effortless ease of use. The unit has a channel selector and two headphone outputs with a single volume control. It allows a meeting chairman to speak, request-to-speak and listen to the speaker in his or her native language. An OLED information display indicates the selected channel number, the abbreviated channel language name in ISO format and a volume bar. This unit is also equipped with an RFID card reader for identification. This is ideal for meetings

with a free seating policy: the system can keep track of who is seated where. The chairman version has 2 additional buttons compared to the delegate unit: "Next-in-line" and "Priority". From this unit, the chairman can also control the overall system volume. The units interconnect in daisy chain over Cat 5e Plixus® network cabling. The RJ45 connectors are hidden in the base of the unit and the cables are held in place by two notches in the unit housing.

Benefits

The Confidea T-CI is a *sleek and stylish solution* and can be set up in the blink of an eye. The

input and output connections are *auto-sensing and interchangeable*. As a result, installation is *easy, fast, and straightforward*, making it the ideal system for frequently changing environments. The removable microphone is *immune for mobile phone interference*, so delegates can leave their phones switched on during the meeting. The Confidea T-CI is backed by the Plixus® network with redundant cabling and hot swapping options to ensure *maximum reliability*. Finally, its shielded microphone is immune to mobile phone interference.

Features

- Built-in high-quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback
- Microphone On/Off or request-to-speak button with two signaling LEDs
- Two headphone outputs with single volume control
- OLED information display with selected language and volume bar
- RFID card reader
- Priority button
- Next-in-line button
- Overall system volume control

Connectivity

- Screw-lock socket to connect a removable microphone.

D-MIC30SL **71.98.0053**

D-MIC40SL **71.98.0054**

D-MIC50SL **71.98.0055**

- Two RJ 45 connectors for loop through cabling
- Two 3.5 mm stereo jack sockets for headphones
- Plixus-powered

Software

To fully configure, manage, and use the unit, Televic's CoCon management software is required. The following standard licenses are available:

CoCon Discussion	71.98.1101
CoCon Authentication	71.98.1105
CoCon Interpretation	71.98.1107

Certifications

Region	Certification
Europe	CE

Specifications

Mechanical	
Material	PC/ABS
Color	Black Matt, RAL9011
Size (mm)	230 (w) × 130 (h) × 60 (d)
Size packed (mm)	250 (w) × 150 (h) × 90 (d)
Weight (g)	480
Weight packed (g)	620
Electrical	
Voltage	48 VDC
Consumption	3.5 W
Speaker Output	
Maximum output power	> 1 W
Frequency response	200-20,000 Hz
Dynamic range	> 90 dB
THD @ nominal level	< 0.1%
Load impedance	8 Ω
Headphone Output	
Maximum output	> 10 mW
Frequency response	22-22,000 Hz
Dynamic range	> 90 dB
THD @ nominal level	< 0.1%
Load impedance	16-32 Ω
Microphone Input	
Nominal input level	-54.7 dBV
Maximum input level	-24.6 dBV
Input impedance	1 kΩ
Dynamic range	> 93 dB
Frequency response	25-20,000 Hz
THD @ nominal level	< 0.1%

All information copyright **Televic Conference**, 2015. Version 1.0, October 2015

—
 Leo Bekaertlaan 1 · 8870 Izegem · Belgium
 Tel. +32 51 30 30 45
 Fax +32 51 31 06 70
 E-mail: conference@televic.com
 Web: <http://www.televic-conference.com>
Televic reserves the right to change this document without notice.